

AX84 Amplifier Revised: Tuesday, November 09, 1999			
Revision: 11			
AX84			
The Cooperative Tube Guitar Amp Project			
http://www.intsys.net/ax84			
Bill Of Materials December 15,1999 4:24:22			
Item	Quantity	Reference	Value
1	4	C1,C7,C12,C13	47uF/350V
2	1	C2	270pF
3	1	C3	0.022uF
4	1	C5	470pF
5	2	C6,C8	0.015uF
6	2	C9,C10	1uF/25V
7	1	C11	100uF/25V
8	2	D1,D2	1N4007
9	1	F1	1A SLO-BLO
10	2	J2,J1	PHONEJACK
11	1	J3	POWER CONNECTOR
12	1	R1	10K/1W
13	3	R2,R3,R4	100K
14	2	R7,R5	1K/1W
15	1	R6	5.6K
16	1	R8	68K
17	2	R9,R13	470K
18	1	R10	2.2MEG
19	1	R11	1MEG
20	1	R12	1.5K
21	1	R14	820
22	1	R15	130/1W
23	1	R16	100/1W
24	1	R17	220K/1W
25	2	R18,R19	100
26	1	S1	SW 3POS
27	1	S3	SW SPST
28	1	S4	SW DPDT
29	1	T1	OT-5SE (Hammond 125E or equiv)
30	1	T2	HAMMOND 269EX
31	1	VR1	250K LIN
32	2	VR2,VR3	1MEG LOG
33	1	VR4	25K LIN
34	1	V1	12AX7A
35	1	V2	EL84